



Philips Pronto

Pronto

SBCRU960



## Clear performance, powerful control

The Pronto control panel replaces a table full of remotes! The programmable, elegant unit is compatible with virtually any brand of A/V equipment. The new high-contrast monochrome display ensures an easy-to-read solution.

### Single control solution for any device, any brand

- Extensive infrared code database for any device or brand
- Convenient infra red learning from another remote by pointing to it
- Radio frequency works through walls and from other rooms
- Additional functionality through future software upgrades

### Fully customisable user interface

- High-contrast easy-to-read monochrome display
- Multiple commands combined in one-touch control
- PC software to create your own user interface

### Great convenience

- LCD screen has backlighting for convenience in the dark
- Cursor keys simplify navigation through on-screen menus
- Settings and codes are retained when replacing the batteries
- Sensor reacts to ambient light to adjust backlighting



# PHILIPS

## Technical specifications

### Picture / Display

- **Diagonal screen size (inch):** 3.8 inch
- **Display colours:** 16
- **Backlight**
- **Backlight colour:** White
- **Resolution:** 320 x 240 pixels
- **Touch panel**
- **Display screen type:** LCD TFT

### Infrared Capabilities

- **Operating distance:** 33 ft (10 m)
- **Learning IR codes**
- **Learning frequency range:** Up to 78 kHz and 455 kHz
- **Transmitting LEDs:** 4
- **Universal infra red code database**
- **Number of brands in database:** Over 1100

### RF Capabilities

- **Addresses (ID's):** 16
- **Channels:** 4
- **Communication:** 1-way
- **Frequency (MHz):** 433

### Customisation

- **Editor application on PC:** ProntoEdit NG
- **On screen customisation**
- **Full screen configurability**
- **Transparency**
- **Macros:** Up to 250 steps
- **Alpha-blending:** No

### Connectivity

- **USB:** USB 1.1

### Convenience

- **Automatic power off**
- **Clock with calendar**

- **Cursor key**
- **Hard buttons**
- **Programmable timers:** 20
- **Gentle fade out of light**
- **Multi language:** GB, D, F, E, NL
- **Pick up sensor:** No

### Dimensions

- **Master carton weight:** 3.8 kg
- **Master carton quantity:** 2
- **Product dimensions (W x H x D):** 92 x 153 x 27 mm
- **Product weight:** 0.260 kg
- **Temperature range (Operation):** +5°C/+45°C

### System Specifications

- **CPU:** Mitsubishi 16 bit
- **Flash memory size:** 4 MB

### System Requirements

- **CD-ROM drive**
- **Hard disc space:** 75 MB
- **PC OS:** Windows 98 SE, 2000, ME, XP
- **RAM memory:** 64 MB
- **USB:** Free USB port

### Accessories

- **Batteries:** Ni-MH battery pack
- **Printed user guide**
- **USB cable**
- **User Guide on CD-ROM**
- **Warranty card**
- **Docking Station**

### Power

- **Charging time:** Max 3 hr
- **Mains power:** 230V

## Product highlights

### Universal infra red code database

A universal IR code database refers to a library of infrared codes built-in to a particular remote. This feature allows a remote to control your equipment without needing to learn individual signals. Select the correct infrared code sets in the database for the devices you want to control, to enable control of virtually every audio/video system element on the market today – regardless of model or brand.

### Learning functionality

Learning functionality refers to the process through which a remote control captures and stores infrared signals from other remotes for later use. When device codes are not included in the on-board database, they can always be learned from the original remote, simply by pointing to it.

### One touch convenience

One-touch convenience allows you to perform multiple commands with one press of a button via a macro. A macro combines a string of pre-programmed commands under one single button. Therefore, it simply takes one button press to execute a series of functions.

### Radio frequency

A radio technology that allows you to control components not in direct line of sight, such as through walls or other obstacles. There are two types of RF used in remote controls: RF to component, and RF to infrared.

### Light sensor

Light sensor is a feature that automatically activates the backlight when the ambient lighting reaches a certain level.

### PC software included

### Backlight on screen

Backlighting is a feature that illuminates the LCD screen or keypad for use in the dark. The two most common types of backlighting include LED and electroluminescent (EL). Remotes backlit with LEDs are typically bright but uneven with a yellow or green colour, while EL panels are smooth with blue, white or green shades.

### Cursor keys

### Memory backup

All settings and learned codes are stored in non volatile memory which does not need power to function and store codes and settings.

### Future proof

To keep your device up to date and enhance its functionality you can download new software that become available. Connect the device to the Internet, either directly or through a PC, and launch the upgrade utility.

### High-contrast display

High-contrast monochrome display includes special technology to increase light output and contrast ratio. Instead of traditional electrofoil backlighting, LEDs are used to offer much higher light output. Contrast is enhanced because of white backlight instead of the traditional green backlight colour. This results in much improved readability of the screen.



Date of issue 2006-03-10

Version: 1.0

12 NC: 9082 100 80137  
EAN: 87 10895 91152 8

Specifications are subject to change without notice.  
Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.  
© 2006 Koninklijke Philips Electronics N.V.  
All Rights reserved.  
[www.philips.com](http://www.philips.com)